



Current Equipment Type

TYPE 6AK6
 MINIATURE
 POWER PENTODE



B7G Base



The BRIMAR type 6AK6 is a miniature output pentode with low heater consumption suitable for use in both AC and AC/DC equipment. It is particularly suitable where power economy and small physical size are of prime importance.

RATINGS

Heater Voltage	6.3 volts
Heater Current	0.15 amp.
Anode Voltage	275 volts max.
Anode Dissipation	2.75 watts max.
Screen (g_2) voltage	250 volts max.
Screen Dissipation	0.75 watts max.
D.C. Cathode Current	21 mA max.

OPERATING CHARACTERISTICS (CLASS A)

Anode Voltage	180 volts
Anode Current	15 mA
Screen Voltage	180 volts
Screen Current	2.5 mA
Control Grid (g_1) Voltage	-9 volts
Cathode Bias Resistor	520 ohms
Anode Impedance...	200,000 ohms
Mutual Conductance	2.3 mA/V
Inner Amplification Factor (μ_{g_1, g_2})	10.5
Optimum Load	10,000 ohms
Power Output	1.1 watts
Harmonic Distortion	10 per cent

Type 6AK6 is a commercial equivalent to the CV1762

