



T.			U_f	I_f	U_{tr}	U_o	U_p	$I_{a(max)}$	I_o	I_p	Fig. ¹⁾	
			V	A	V	V	V	mA	mA	mA	n ^o	
BT-129 ГГ 1-0,5/5	CCCP CCCP	1 2	2,38 ÷ 2,75 2,4 ÷ 2,7	9 8,5	{	6400 3200	2850 1425	9000 9000 9000	500	500 1000	1500	1
												2
RX 21	Eim	3	2,5	10	{	7100 3550	3200 3200	10000 750	750	3000 3000	1 2	
VH 6300	SFR	4	2,5	10				10000 10000	750 1500	750		1500
2 V/401 B	STCE	1	2,7	8,25	{	1400 2800 1630 1630 1630	1270 2540 1910 1910 3820	4000	500	1500	2 3 4 5 6	
3 B 25	amer	5	2,5	5				4000 4000 4000 4000 4000	500 500	1000 1000 1500 3000 1500		

T.	Image	Image	U_f	I_f	U_{tr}	U_o	U_p	$I_{a(max)}$	I_o	I_p	Fig.1)
			V	A	V	V	V	mA	mA	mA	n ⁰
249 B	WE	6	2,5	7,5							
258 B	WE	7	2,5	7,5			7500	640		2500	
3017 B	LCT	1	2,5	7,5			7000	500		1500	

1) vide gr. 58 a

Equivalents

BГ-1,5/5000	CCCP = ГГ1-0,5/5	RX 21-A	Eim = RX 21	249 C	Amp = 249 B
BГ-9	CCCP = BГ-129	T 249	Tay = 249 B	258 A	WE = 258 B
BГ-10	CCCP = ГГ1-0,5/5	249 A	WE = 249 B	4017 B	STCE = 2 V/401 B

