



T.			U_f	I_f	U_p	$I_a(max)$	I_p	P_a
			V	A	V	mA	mA	W
A 207	EEV	1	4	12	40000	350	1100	130
A 237	EEV	1	4	12	65000	250	1500	
ESU 74	Maz	1	4	11,5	40000	210	1100	50
152-R	Eim	2	5	13	30000	150		
221-A	amer	2	5	10	25000	300	1500	
250-R	Eim	2	5	10	60000	250	2500	150
8020 ¹⁾	amer	3	5	6	40000	100	750	75
RA 100 A	Tes	1	5	6,5				

¹⁾ $U_{tr} = 14000$ V, $U_o = 17000$ V, $I_o = 80$ mA, (8020×1)

Equivalents

B 1-0,1/40	CCCP = 8020	2-150 D	Eim = 152-R
B-40/100	CCCP = 8020	2-250 A	Eim = 250-R
ESU 77	Maz = A 207	100-R	Eim = 8020
GL-451	GE = 8020	152-RA	Eim = 152-R
ML-371	Mch = 221-A	371 B	amer = 221-A
RY 12-100	Mul = 8020	451	amer = 8020
2-100 A	Eim = 8020	578	RCA = 8020
2-150 A	Eim = 152-R	56000	amer = 8020

