



T.			U_f		Cl.	U_a	U_{g2}	U_{g3}	U_{g1}	I_a	I_{g2}	I_{g1}	$U_{g1 \approx}$	P_{dr}	P_o	P_{g2}	P_a
			V	A													
PE 1/80	Ph1	1	12	0,9	C-Tgr	750 1000	350 300	40 0	-170 -170	130 97	9 10	6 5	205 200	1,25 1	70 73	3,1 3	27,5 24
PV 1-35	Mu1	2	12	0,9	C-Tlf; A-Mod C-Tlf; G ₂ -Mod C-Tlf; G ₃ -Mod stat.	1000 1000 1000	275 250 300	0 0 -120	-170 -170 -170	43 55 41	21 2 20	5,3 1,5 2,6	200 190 190	1,1 0,3 0,5	32 21 11	5,8 0,5 6	11 34 30
						1000 1000	200 500			40 115	30 14					6 6	35 35

$S = 2,3 \text{ mA/V}; \mu_{(g2/g1)} = 4$
 $f = 20 \text{ MHz}$



PE1/80



PVI-35

Equivalent PV 1-35

SW 35 PEN	Maz
-----------	-----

T.	C_{g1}		C_a	$C_{g1/a}$	
	pF	pF		pF	pF
PE 1/80	15	12	12	0,1	
PV 1-35	15	11	11	0,12	