CATHODE RAY TUBE

MINISTRY OF SUPPLY

(ACR23A)

Specification MOS, Dated 1.6.46. To be read in con.	Specification C.R.T. Restricted Restricted			
		ndicate	s a change	
TYPE OF DEFLECTION	MARKING			
BULB: -	Internally coated with conductive coating.	i	See K1001/4	
SCREEN: -	Afterglow. BYI46			
RATING		Note	BASE 12 contact key base	
Heater Voltage Heater Current Max. Final Anode V Desirable Spot Siz X plate sensitivit Y plate sensitivit	$\begin{array}{ccc} \text{Ze} & (mm) & 1.0 \\ \text{Zy} & (mm/V) & 1000 \\ \hline V_{A3} & & & \\ \end{array}$		DIMENSIONS CONNECT ONS See drawing on Page 4.	
TYPICAL OPERATING	CONDITIONS		·	
Final Anode Voltag Second Anode Volta Beam Current				

NOTE


- A:- A magnetic shield shall be supplied fitted to the tube and be such as to provide adequate screening from external magnetic fields.
- B:- When viewing the screen with the tube positioned such that the base spigot is uppermost, a positive voltage applied to the terminal X₁ shall deflect the spot to the right, and a positive voltage applied to the terminal Y₁ shall deflect the spot downwards.
- C:- CV1399 (ACR23A) and CV1398 (ACR23) differ only in that the former has the screen markings shown in drawing on page 4.

TESTS

To be performed in addition to those applicable in K1003.

ည္က	Test Conditions						mits	No.
Clause	$v_{\mathbf{h}}$	V _a 3 (kV)	V _{a2}	Vg	Tests	Min.	Max.	Test- ed
(a)					Capacitances (pf) 1. Each X or Y plate to all other electrodes 2. Grid to all other electrodes 3. One X to one Y plate	-	20 20 5	Type Ap- prov- al Test only
(b)	4.0	0	O	0	$I_{\mathbf{h}}$ (A)	.75	1.2	100%
(c)				e give a equal dard of in the in the	1. The line width shall not be greater than that of standard tube 2. Va2 (kV) 3. Vg (V)	.3 .6 To be at least 1v negative to cathode		100%
(a)	4.0	2.0	As in (c)	Ad- justed to give cut-off	1. Vg (V) 2. Increase in negative value of Vg compared with value noted in (c) 3	7,33	-31 10	100%
(e)	Reco	K100	As in (c) ded med 3. Cla Insert = 5 med	thod:- ause t	Grid Insulation Leakage current (µA) Increase in voltmeter reading		6.2 100%	100%
(f)	4.0	2.0	As in (c)	Any con- venient value	Deflection Sensitivities 1. X plate (mm/V) 2. Y plate (mm/V)	800 Va3 300 V _{a3}	1250 V _a 3 1250 V _a 3	10%
(g)	4.0	2.0	As in (c)	Any con- venient value	Deviation of spot from centre of screen. (mm)	-	15	100%

				<u> </u>	<u> </u>			
(h)	Def the	stat tred		cle	Useful Screen Area Radius (mm)	105		100%
(3)	Ang:	2.0 le me to ring	As in (c) easured axis 00	Any convenient value rela-	Orientation of Y axis of deflection		<u>+</u> 10°	100%
(k)	4.0	2.0	As in (c)	Any con- venient value	Angle between X and Y axis	88 °	920	10%
(1)	4.0 2.0 As in As in (c) Test to be done by an approved method			(c) by an	The screen shall not be worse for graini- ness, non-uniformity and afterglow than the corresponding standard tube	,		100%
(m)	4.0	4.0	See C] 5.14 C	lause of K1003	Over Voltage Test			100%
(n)	4.0	2.0	As in (c)	Adjusted to give normal bright-ness raster		1000	-	1%
	Deflection to cover a			cover a				
	raster of area							
	210 x 210 mm.							



LINES NOT MORE THAN 50 WIDE, DRAWN IN BLACK ENAMEL (SUPERIOR BERLIN BLACK FROM CHARLES TURNER & SONS, BLOOMSBURY HOUSE, HICH HOLBORN) - WHOLE FACE OF TUBE SPRAYED AFTER MARKING WITH CLEAR VARNISH, MAKERS REF. K 371 158 1 5.0. D4 2427 FROM JENSON & NICHOLSON LTD. STRATFORD, E.IS. - THE CROSS LINES CORRESPOND TO THE ELECTRICAL AXES OF THE TUBE, & ARE THEREFORE NOT NECESSARILY ACCURATELY AT 90° TO EACH OTHER), THE POINT OF INTERSECTION & THE CENTRE OF THE CIRCLE TO ITS ELECTRICAL CENTRE.