

SAN CARLOS, CALIFORNIA

4CX600A

(formerly X2009)

The 4CX600A is a compact radial-beam tetrode with low lead inductances and low interelectrode capacitances, designed for use in distributed amplifiers and in UHF service up to 1300 Mc. Maximum plate dissipation is 600 watts.

A feature of this tube is the integral screen-cathode by-pass capacitor. One side of the heater is terminated in a "deck" attached to this capacitor while the other heater contact is brought out on a pin on the tube base. The control grid is brought out to four threaded pins on the base.

GENERAL CHARACTERISTICS

Volts	6.0	-	-	-	-	-	Heater Voltage				
Amperes	4.8	-	_	_	-	-	Current (average) -				
						al	Cathode: Oxide-coated, Unipotentia				
- 8	-	-	-	-	-	-	Amplification Factor				
umhos	25,000	- 5	-	-	-	-	Transconductance (I _b = 300 mA)				
Mc	1300	-	_	-	-	_	Frequency for maximum ratings				
							Interelectrode capacitances:				
uuf	42	-	_	-	-	-	Input				
uuf	10	-	-	_	-	_	Output				
uuf	110	_	_	_	_	_	Screen-cathode				

MECHANICAL

ELECTRICAL

Base	-	-	-	-	-	-	-	-	-	5	Pin, Spec	cial
Maxir	num ope	rating t	emper	atures:								
	Anode	_	_	_	-	-	_	-	-	-	250°	C
	Ceran	nic-met	al seal	s -	-	_	-	-	-	-	250°	C
Cooli		_	_	_	_	-	-	-	-	-	Forced	air

MAXIMUM RATINGS Class-C Amplifier

DC Plate Voltage-	-	-	-	-	_	-	-	3000	Max.	Volts
DC Screen Voltage	-		-	_	-	-	_	400	Max.	Volts
DC Grid Voltage -	-	_	-	-	-	-	-	-150	Max.	Volts
DC Plate Current	-	_	-	-	-	-	-	500	Max.	mA.
Plate Dissipation-	-	-	-	-	-	-	-	600	Max.	Watts
Screen Dissipation	-	-	-	-	-	-	-	15	Max.	Watts
Grid Dissipation -	-	-	-	-	-	-	_	3	Max.	Watts

This information applies to a tentative tube design and is subject to change. Further application information is available from Power Grid Tube Marketing, Eitel-McCullough, Inc., San Carlos, California.

