

12HG7

SHARP-CUTOFF PENTODE

RCA Dark Heater Frame-Grid Construction For Video-Output Amplifier Service in Calor-TV Receivers

Mechanical:

g_m = 32000 µmhos Ph = 10 watts

RCA-12HG7 is a frame-grid type sharp-cutoff pentode in a T9 envelope utilizing a large-button neonoval 9-pin base. This type is especially useful as a videooutput amplifier tube in color-TV receivers.

The 12HG7 incorporates a special large-area plate structure which, in combination with the T9 envelope, provides a dissipation capability of 10 watts. Because of this high dissipation capability, it is possible to eliminate a series plate-circuit dropping resistor and its associated bypass capacitor in new-equipment circuit designs.

The frame-grid construction of the 12HG7 provides an exceptionally high value of transconductance (32000) µmhos). This tube also features a plate current characteristic with controlled knee to provide good linearity at relatively low plate voltage.

The 12HG7 utilizes an RCA Dark Heater to provide long and dependable performance.

GENERAL DATA

Parallel

Series

_			٠			
ᆫ	ıe	ctr	10	: a	ŧ:	

Heater Characteristics	and	Ratings:
Heater-section arrange	emei	nt

Voltage (AC or DC)	$12.6 \pm$	1.3	6.3 ± 0.6	volts
Current at bogey voltage	0.260	0.	520	amp
Peak heater-cathode voltage:				
Heater negative with respect to cathode	200	max	•	volts
Heater positive with respect to cathode	200°	max		volts
Direct Interelectrode Capacitances:b				
Grid No.1 to plate	0.12	max		pf
Input: G1 to $(K,G3+IS,G2,H)$	14.0			pf
Output: P to (K,G3+IS,G2,H)	4.4			pf
Characteristics, Class A, Amplifier:				

Characteristics, Class A ₁ Amplifier:		
Plate Supply Voltage	300	volts
Grid No.3 Conne	cted to	cathode at socket
Grid-No.2 Supply Voltage	135	volts
Grid No.1 Connected to negative	ve end	of cathode resistor
Cathode Resistor	47	ohms
Plate Resistance (Approx.)	60000	ohms
Transconductance	32000	μ mhos
Plate Current	31	ma
Grid-No.2 Current	4.8	ma
Grid-No.1 Voltage (Approx.) for plate $\mu a = 100 \dots$	-4.5	volts

a The dc component must not exceed 100 volts.

Operating Position Any Type of Cathode Coated Unipotential

Maximum Over-all Length 2.930" Maximum Seated Length........... 2.620" Length, Base Seat to Bulb Top (Excluding tip). 2.070" to 2.310"

Diameter 1.062" to 1.188" Dimensional Outline. JEDEC No.9-70

Base. Large-Button Neonoval 9-Pin (JEDEC No.E9-68)

AMPLIFIER - Class A1

Maximum Ratinas, Design-Maximum Values;

Plate Voltage	400 max.	volts
Grid-No.2 (Screen-Grid) Supply Voltage	330 max.	volts
Grid-No.2 Voltage See GRID-No.2 INPU	JT RATING	CHART
Grid-No.1 (Control-Grid) Voltage:		
Positive-bias value	0 max.	volts

10 max. watts Grid-No.2 Input; For grid-No.2 voltages

For grid-No.2 voltage between


165 and 330 volts. See GRID-No.2 INPUT RATING CHART

Maximum Circuit Values:

Grid-No.1-Circuit Resistance:

For fixed-bias operation 0.1 max. megohm For cathode-bias operation 0.25 max. megohm

GRID-No.2-INPUT RATING CHART



GRID-No.2 VOLTAGE EXPRESSED AS PER CENT OF MAXIMUM GRID-No.2-SUPPLY-VOLTAGE RATING 92CS-7586R2




watt.


1 max.

b Without external shield.

AVERAGE CHARACTERISTICS




DIMENSIONAL OUTLINE JEDEC No.9-70




Dimensions in Inches

- MEASURED FROM BASE SEAT TO BULB-TOP LINE AS DETERMINED BY A RING GAUGE OF 0.600" I.D.
- ** APPLIES IN ZONE STARTING 0.375" FROM BASE SEAT.

AVERAGE CHARACTERISTICS



TERMINAL DIAGRAM Bottom View



JEDEC 9BF

Pin 1 - Cothode
Pin 6 - Heater Tap
Pin 2 - Grid No.1
Pin 7 - Plate
Pin 8 - Grid No.2
Internal
Shield
Pin 9 - Grid No.3,
Internal
Shield

Pin 5 - Heater

Information furnished by RCA is believed to be accurate and reliable. However, no responsibility is assumed by RCA for its use; nor for any infringements of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of RCA.